D2L108 QUENCH TESTS



20-Oct-2003
J. F. Muratore
Brookhaven National Lab

D2L108 QUENCH SUMMARY

Magcool Bay C

QUENCH #	RUN #	CURRENT (A)	T1 (K)	T3 (K)	START (ms)	MIITS	COIL	COMMENTS
T = 4.5K (nom)								
Warm bore tubes installed, sealed, and under vacuum								
Forced flow cooling @ 12atm								
1	17	6355	4.526	5.070	-34	9.2	upper right	
2	18	6619	4.574	5.155	-22	9.1	lower right	
Warm bore tubes open								
Magnetic field measurements to 6400A with no quenches								
Switched to liquid helium bath cooling @ 1.4atm								
Warm bore tubes sealed and under vacuum								
3	56	6781	4.543	4.539	-17	7.8	upper left	

Notes:
a) Ramp rate for quenches was 20A/s.
b) Energy extraction used: 35mohms for all quenches.
c) The temperature T1 is a diode sensor located in the helium return line tube which contains the superconducting bus; T3 is in the lower lead interconnect pot. Both have associated redundant sensors.
d) There were no auxiliary voltage taps in the magnet coils.
e) Data acquisition sampling rate was 1kHz for all quenches.
f) Strip heaters were fired at 475V (nom) and 96A (nom), with 1ms delay.
g) For all quenches, the voltage difference quench detector threshold voltage was set at 0.6V.
h) For quenches #2 and #3, some voltage spikes were seen prior to the quench but not at the quench start.